

## ● Part Numbering

### Chip Ferrite Beads

(Part Number)

|           |          |           |           |            |          |          |          |          |
|-----------|----------|-----------|-----------|------------|----------|----------|----------|----------|
| <b>BL</b> | <b>M</b> | <b>18</b> | <b>AG</b> | <b>102</b> | <b>S</b> | <b>N</b> | <b>1</b> | <b>D</b> |
| ①         | ②        | ③         | ④         | ⑤          | ⑥        | ⑦        | ⑧        | ⑨        |

#### ① Product ID

| Product ID |                    |
|------------|--------------------|
| <b>BL</b>  | Chip Ferrite Beads |

#### ② Type

| Code     | Type            |
|----------|-----------------|
| <b>A</b> | Array Type      |
| <b>M</b> | Monolithic Type |

#### ③ Dimensions (L×W)

| Code      | Dimensions (L×W) | EIA  |
|-----------|------------------|------|
| <b>03</b> | 0.6×0.3mm        | 0201 |
| <b>15</b> | 1.0×0.5mm        | 0402 |
| <b>18</b> | 1.6×0.8mm        | 0603 |
| <b>2A</b> | 2.0×1.0mm        | 0804 |
| <b>21</b> | 2.0×1.25mm       | 0805 |
| <b>31</b> | 3.2×1.6mm        | 1206 |
| <b>41</b> | 4.5×1.6mm        | 1806 |

#### ④ Characteristics/Applications

| Code *1   | Characteristics/Applications                      | Series   |
|-----------|---|--|
| <b>AF</b> | for General Use                                   | <b>BLM31/BLM41</b>                               |
| <b>AG</b> |   | <b>BLM03/BLM15/BLM18/BLM21/BLM31/BLA2A/BLA31</b> |
| <b>AJ</b> |   | <b>BLM21/BLM31</b>                               |
| <b>AH</b> |   | <b>BLM21</b>                                     |
| <b>BA</b> | for High-speed Signal Lines                       | <b>BLM18</b>                                     |
| <b>BB</b> |   | <b>BLM15/BLM18/BLM21/BLA2A</b>                   |
| <b>BD</b> |   | <b>BLM15/BLM18/BLM21/BLA31</b>                   |
| <b>BE</b> |   | <b>BLM31</b>                                     |
| <b>PF</b> | for Power Supplies                                | <b>BLM41</b>                                     |
| <b>PG</b> |   | <b>BLM18/BLM21/BLM31/BLM41</b>                   |
| <b>RK</b> | for Digital Interface                             | <b>BLM18/BLM21</b>                               |
| <b>HG</b> | for GHz Band General Use                          | <b>BLM18</b>                                     |
| <b>EG</b> | for GHz Band General Use (Low DC Resistance type) |  |
| <b>HB</b> | for GHz Band High-speed Signal Line               | <b>BLM18</b>                                     |
| <b>HD</b> |   |  |
| <b>HK</b> | for GHz Band Digital Interface                    | <b>BLM18</b>                                     |
| <b>GG</b> | for High-GHz Band General Use                     | <b>BLM18</b>                                     |

\*1 Frequency characteristics vary with each code.

#### ⑤ Packaging

| Code     | Packaging                    | Series   |
|----------|------------------------------|--|
| <b>K</b> | Plastic Taping (ø330mm Reel) | <b>BLM31/BLM41/BLM21</b> *1                            |
| <b>L</b> | Plastic Taping (ø180mm Reel) |  |
| <b>B</b> | Bulk                         | All series   |
| <b>J</b> | Paper Taping (ø330mm Reel)   | <b>BLM15/BLM18/BLM21</b> *2 / <b>BLA31</b>             |
| <b>D</b> | Paper Taping (ø180mm Reel)   | <b>BLM03/BLM15/BLM18/BLM21</b> *2 / <b>BLA2A/BLA31</b> |
| <b>C</b> | Bulk Case                    | <b>BLM15/BLM18</b>                                     |

\*1 BLM21BD222SN1/BLM21BD272SN1 only.

\*2 Except BLM21BD222SN1/BLM21BD272SN1

#### ⑤ Impedance

Expressed by three figures. The unit is in ohm ( $\Omega$ ). The first and second figures are significant digits, and the third figure expresses the number of zeros which follow the two figures.

#### ⑥ Performance

Expressed by a letter.

Ex.)

| Code     | Performance |
|----------|-------------|
| <b>S</b> | Sn Plating  |

#### ⑦ Category

| Code     | Category      |
|----------|---------------|
| <b>N</b> | Standard Type |

#### ⑧ Number of Circuits

| Code     | Number of Circuits |
|----------|--------------------|
| <b>1</b> | 1 Circuit          |
| <b>4</b> | 4 Circuits         |